

LA-UR-15-22102

Approved for public release; distribution is unlimited.

Title: MaRIE Undulator & XFEL Systems

Author(s): Nguyen, Dinh Cong
Marksteiner, Quinn R.
Anisimov, Petr Mikhaylovich
Buechler, Cynthia Eileen

Intended for: MaRIE XFEL Pre-Conceptual Reference Design and Risk Reducing R&D Plan
Review, 2015-03-12 (Los Alamos, New Mexico, United States)

Issued: 2015-03-23

Disclaimer:

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the Los Alamos National Security, LLC for the National Nuclear Security Administration of the U.S. Department of Energy under contract DE-AC52-06NA25396. By approving this article, the publisher recognizes that the U.S. Government retains nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.



MaRIE Undulator & XFEL Systems

Dinh Nguyen
Quinn Marksteiner
Petr Anisimov
Cindy Buechler

March 12th, 2015

UNCLASSIFIED


Outline



- **MaRIE XFEL Performance Parameters**
- **Input Electron Beam Parameters**
- **Undulator Design**
- **Genesis Simulations**
- **Risks**
- **Summary**

UNCLASSIFIED

MaRIE XFEL Performance Parameters



MaRIE Undulator Performance Parameters

- ❑ Produces $>2 \times 10^{10}$ 42-keV photons in each 33-fs pulse
- ❑ Provides standard SASE bandwidth (0.1% relative to λ_0)
- ❑ Provides narrow linewidth ($<0.01\%$ relative to λ_0) option for CXDI

UNCLASSIFIED

Undulator and FEL Radiation Parameters



	Symbol	Value
Undulator period	λ_u	18.6 mm
Undulator magnetic field	B_0	0.7 T
rms (peak) undulator parameter	$K_{\text{rms}} (K_{\text{peak}})$	0.86 (1.22)
FEL resonance wavelength	λ_0	0.2934 Å
FEL (Pierce) parameter	ρ	0.0005
Calculated 3D gain length	L_G	2.6 m
Calculated 3D saturated power	P_S	9 GW
FEL pulse energy at saturation	W_p	0.3 mJ

UNCLASSIFIED

Assumptions





- **Electron beam at undulator entrance has the following properties**
 - Bunch charge = 100 pC
 - Bunch length = 10 μm (33 fs)
 - Peak current = 3.5 kA
 - Normalized emittance (slice) = 0.2 μm
 - rms relative energy spread (slice) = 0.02%
 - No significant energy slew along the bunch
 - No significant microbunching (μBI) due to longitudinal space charge
 - No dispersion of x beam centroid along the bunch

UNCLASSIFIED

Elegant-generated Electron Beam (S-band)



S-band linac electron beam distribution has LSC μ BI suppression





Electron beam at the entrance has a residual energy slew. Lasing occurs over the region where peak current is maximum and energy slew is minimum.

Courtesy of J. Lewellen

UNCLASSIFIED


MaRIE undulators are similar to SwissFEL U15



Courtesy of T. Schmidt

- PM material = VACODYM 863 TP with Dy infusion
- $B_f = 1.25$ tesla; intrinsic $H_c > 2,300$ kA/m
- Pole material = vanadium permendur
- Wakefield shield and RF fingers = 0.1-mm CuNi foils with 50- μ m copper as the RF surface.

Calculated magnetic field vs gap




UNCLASSIFIED


MaRIE XFEL has 14 FODOs with undulators




MaRIE XFEL with Distributed Seeding



Courtesy of R. Ganter



Each 0.6m break between undulator segments houses two gate valves, a beam position monitor, a phase shifter, a PM FODO quad and an adjustable alignment quad.




UNCLASSIFIED

In-Vacuum Undulator Performance Data



	SwissFEL U15	MaRIE
Period (mm)	15	18.6
Maximum B_0 (T)	0.85	0.7
Maximum K_{peak}	1.8	1.49
Nominal gap (mm)	4.7	7.0
Segment length (m)	4.0	3.72
N periods / segment	266	200
Vacuum pressure (torr)	2.6×10^{-7}	
CuNi straightness (μm)	12-18	
CuNi roughness (nm)	120	
Wakefield, flat Cu 5-mm	-50 keV/m/.1nC	
Wakefield, round Cu 5-mm	-150 keV/m/.1nC	

R. Ganter et al., Proceedings of FEL2012 Conference




UNCLASSIFIED

Distributed Seeding with Si(111) Crystals



Si(111) crystals have >90% reflectivity per surface





Bragg angle at 0.294Å is 2.7°

Darwin width = 1.25 arc sec ($\Delta\lambda/\lambda_0 = 1.3 \times 10^{-4}$)


A 0.7- μm slit between double monochromators selects $\pm 0.01\%$ BW

Curved Si crystals ($R = 0.424\text{m}$) focus X-ray beams onto the slit.



UNCLASSIFIED

Chicane synchronizes electrons with X-rays



Delay in electron beam path

$$\Delta S_e = 4L \left(\frac{\theta_e}{\sin \theta_e} - 1 \right) + 2D \left(\sqrt{1 + \tan^2 \theta_e} - 1 \right)$$

Delay in X-ray beam path


$$\Delta S_{X-ray} \approx S_{12} \tan^2(2\theta_B)$$

Electron and X-ray beams are delayed with respect to straight path by 357 μm (1.19 ps)

Chicane R₅₆ also smears out any FEL-induced microbunching (fresh bunch technique).



UNCLASSIFIED

SASE generates 3×10^{10} photons in 0.08% BW



MaRIE XFEL in SASE mode is quasi-coherent temporally. Each FEL pulse contains about one hundred coherence lengths, same as the number of spectral spikes. The overall bandwidth (FWHM) is 0.08% in agreement with prediction.

$$\frac{\Delta\lambda}{\lambda_0} = \frac{4 \ln 2}{\sqrt{\pi}} \rho \approx 1.56 \rho$$



UNCLASSIFIED





How does DS improve spectral contrast?



Angle-integrated undulator radiation with real electron beams starts out with many photons at wavelengths longer than λ_0 (equivalent to ε_c)

As SASE builds up, spectrum becomes more Gaussian and shifts to shorter λ

SASE power (log) versus distance




Seeding at longer λ (but within gain bandwidth) increases the seeded FEL signal relative to SASE background, thus improving the spectral contrast.



UNCLASSIFIED



DS generates 2×10^{10} photons in 0.008% BW





Seeding earlier in the power vs z curve at more than one location produces narrow FEL linewidth and low SASE background.



UNCLASSIFIED

Different DS schemes yield similar performance





All Distributed Seeding schemes yield the same number of photons and relative bandwidth. The worst performer is single-step self-seeding (purple traces) which yields fewer photons and larger rms bandwidth.

UNCLASSIFIED



Risk 1 – I_{peak} is too low

- **Cause**: Can't compress electron bunch in BC2 with good ε_n and $\Delta\gamma/\gamma$.
- **Consequence**: Number of photons in 100-pC bunch drops to 1×10^8 (undulator radiation with medium peak current in long undulators).
- **Mitigation**: Increase bunch charge and/or undulator length.




UNCLASSIFIED

Slide 16



Risk 2 – Beam ε_n and $\Delta\gamma/\gamma$ don't meet specs

- **Cause**: Can't achieve the specified ε_n (0.2 μm) and $\Delta\gamma/\gamma$ (0.02%).
- **Consequence**: Number of photons / bunch is affected.
- **Mitigation**: Taper the undulator to recover the number of photons.





UNCLASSIFIED

Slide 17



Risk 3 – CSR in delay chicane is too high

- **Cause**: CSR reduces the beam energy where lasing occurs.
- **Consequence**: Number of photons / bunch is reduced.
- **Mitigation**: Reduce number of filters (chicanes); taper the undulator.



UNCLASSIFIED

Slide 18



Risk 4 – Broad spectrum from DS FEL

- **Cause**: Incomplete dechirping, large energy spread or CSR in chicanes.
- **Consequence**: Output bandwidth ($\sim 0.08\%$) is too large for CXDI.
- **Mitigation**: Perform early validation experiments.

UNCLASSIFIED


Slide 19



Risk 5 – LSC causes too much microbunching

- **Cause**: LSC microbunching is significant after BC2.
- **Consequence**: Larger SASE bandwidth. DS may not work.
- **Mitigation**: Model DS using electron beams with μ BI.

μ BI causes strong modulation in P vs s plot. The SASE peak power is higher but the spectrum is broader.




UNCLASSIFIED

Slide 20



Risk 6 – Resistive wake is too high

- **Cause**: Resistive wake is higher than Bane-Stupakov prediction.
- **Consequence**: Number of photons / bunch is reduced.
- **Mitigation**: Taper the undulator; perform validation experiments.



UNCLASSIFIED

Slide 21

Summary



- Time-dependent Genesis simulations show the MaRIE XFEL can deliver the number of photons within the required bandwidth, provided a number of assumptions are met.
- The highest risks are associated with the electron beam driving the XFEL undulator.
- Risks associated with the undulator and/or distributed seeding technique may be evaluated or retired by performing early validation experiments.

UNCLASSIFIED

Slide 22